






<div>inter•lux</div>		Vertical Plaster Cove INSTALLATION INSTRUCTIONS		WEIGHT:	FINISH: White (Standard)	WG VBC-RPT			
<div><div>WARNING: INSTALL PRODUCT IN ACCORDANCE WITH LOCAL AND NATIONAL ELECTRICAL CODES BY A QUALIFIED ELECTRICIAN OR ELECTRICAL CONTRACTOR.</div></div>		<div><div>WARNING: FAILURE TO COMPLY WITH THE INSTALLATION INSTRUCTIONS MAY RESULT IN DEATH OR SERIOUS INJURY</div></div>		<div><div>WARNING: READ ALL SAFETY INSTRUCTIONS INCLUDED WITH LUMINAIRE BEFORE INSTALLING LUMINAIRE.</div></div>		<div>CAUTION: THIS IS AN ELECTRONIC DEVICE. CARE MUST BE TAKEN DURING STORAGE AND HANDLING. STORE IN A CLEAN, COOL AND DRY LOCATION. ELECTROSTATIC DISCHARGE (ESD) CAN HARM THIS PRODUCT. AVOID STATIC DISCHARGE WHILE HANDLING THIS PRODUCT.</div>		<div>CAUTION: INTER-LUX IS NOT RESPONSIBLE FOR THE STRUCTURAL INTEGRITY OF THE BUILDING TO SUPPORT THE LUMINAIRE. ADDITIONAL BACKING MAY BE REQUIRED.</div>	

ISOMETRIC VIEWS




MOUNTING DIMENSIONS




MOUNTING OPTIONS



PACKAGE MAY INCLUDE: (refer to package list to identify parts)



ITEMS NEEDED (SUPPLIED BY OTHERS):




INSTALLATION INSTRUCTIONS


LOCATE AND REVIEW ANY CONSTRUCTION PLANS AND INTERLUX RECORD DRAWINGS FOR ALL FIXTURE RUNS.

It is recommended to locate and lay out all components for each fixture "run". A fixture run typically consist of joiners, lengths of housings, lengths of gear trays with diffuser(satellite and master), blank gear trays, endcaps, in-fill panels and L-angles. BE SURE TO IDENTIFY ALL CORRECT LENGTHS FOR EACH FIXTURE RUN.


Step 1: Turn off Power before Installing. **MOUNTING:**Mount L-Angle Bracket to intended illuminated surface at height using appropriate mounting screws at 48" o.c. Mount housing extrusion to the mounting surface using appropriate mounting screws at 16" o.c. Surrounding structure is required to support the weight of the fixture.




Step 2: (If single housing skip this step) Insert joiners into next housing as seen below.Place next housing end to end with first housing, slide joiners across housing seam so they are joining both housings. Secure joiners by tightening set screws. Mount housing. Repeat until all housing are installed and mounted.




Step 4: Attach 5/8" drywall to the underside of the housing. Apply joint tape and mud to form a smooth taper. Apply multiple thin coats to ensure a smooth taper. Prime and paint.




Step 4: (If no endcaps skip this step). Install endcaps on first and last housing. Secure by tightening set screws.



Step 5: (If no Infill panels skip this step). Install Infill panels. Secure using provided M4 fasteners and pre-machined holes as seen below.



Step 6: Install Gear Trays making electric connections first then insert gear tray into housing. Refer to pages 2&3 for wiring diagrams if needed. Refer to record drawings for gear tray placement. Secure gear tray to housing using screws in pre-drilled holes. Repeat this step until all gear trays are installed. Energize and test for proper operation.



Vertical Plaster Cove

INSTALLATION INSTRUCTIONS

WEIGHT:

FINISH:

White (Standard)

WG VBC-RPT

WARNING:
INSTALL PRODUCT IN ACCORDANCE WITH LOCAL AND NATIONAL ELECTRICAL CODES BY A QUALIFIED ELECTRICIAN OR ELECTRICAL CONTRACTOR.

WARNING:
FAILURE TO COMPLY WITH THE INSTALLATION INSTRUCTIONS MAY RESULT IN DEATH OR SERIOUS INJURY

WARNING:
READ ALL SAFETY INSTRUCTIONS INCLUDED WITH LUMINAIRE BEFORE INSTALLING LUMINAIRE.

CAUTION:
THIS IS AN ELECTRONIC DEVICE. CARE MUST BE TAKEN DURING STORAGE AND HANDLING. STORE IN A CLEAN, COOL AND DRY LOCATION. ELECTROSTATIC DISCHARGE (ESD) CAN HARM THIS PRODUCT. AVOID STATIC DISCHARGE WHILE HANDLING THIS PRODUCT.

CAUTION:
INTER-LUX IS NOT RESPONSIBLE FOR THE STRUCTURAL INTEGRITY OF THE BUILDING TO SUPPORT THE LUMINAIRE. ADDITIONAL BACKING MAY BE REQUIRED.

AC Power

Neutral (White)

Line (Black)

Ground (Green)

Dimming + (Purple)

Dimming - (Grey)

Switch/Dimmer (if applicable)

Master Gear Tray

Maximum Wiring Distance*

Wire Gauge	Maximum Lead Length			
	Osram			Lutron
	≤ 48W	≤ 72W	≤ 96W	≤ 40W
#18AWG	37'	25'	18'	15'
#16AWG	59'	39'	29'	25'
#14AWG	95'	63'	47'	40'
#12AWG	151'	101'	75'	60'

*Actual Voltage drop to be calculated by installer

Red	Blue	Green	Black	White	Purple	Grey
Positive	Negative	Ground	Line	Neutral	Dimming +	Dimming -

Standard Non-Dimming/DFPN Dimming

D3W 1% Dimming

DES 1% Dimming

0-10V Dimming

Phone: (410)381-1497

Web: www.inter-lux.com




PROPRIETARY AND CONFIDENTIAL

THE INFORMATION CONTAINED IN THIS DRAWING IS THE SOLE PROPERTY OF **inter-lux**. ANY REPRODUCTION IN PART OR AS A WHOLE WITHOUT THE WRITTEN PERMISSION OF **inter-lux** IS PROHIBITED.

SHEET 2 OF 3

DRAWING NOT TO SCALE REV N/C

*Inter-lux reserves the right to make changes to this product and related installation instructions at any time without prior notice.

<div>inter•lux</div>		Vertical Plaster Cove INSTALLATION INSTRUCTIONS		WEIGHT:	FINISH: White (Standard)	WG VBC-RPT	
<div><div></div><div>WARNING: INSTALL PRODUCT IN ACCORDANCE WITH LOCAL AND NATIONAL ELECTRICAL CODES BY A QUALIFIED ELECTRICIAN OR ELECTRICAL CONTRACTOR.</div></div>		<div><div></div><div>WARNING: FAILURE TO COMPLY WITH THE INSTALLATION INSTRUCTIONS MAY RESULT IN DEATH OR SERIOUS INJURY</div></div>		<div><div></div><div>WARNING: READ ALL SAFETY INSTRUCTIONS INCLUDED WITH LUMINAIRE BEFORE INSTALLING LUMINAIRE.</div></div>		<div>CAUTION: THIS IS AN ELECTRONIC DEVICE. CARE MUST BE TAKEN DURING STORAGE AND HANDLING. STORE IN A CLEAN, COOL AND DRY LOCATION. ELECTROSTATIC DISCHARGE (ESD) CAN HARM THIS PRODUCT. AVOID STATIC DISCHARGE WHILE HANDLING THIS PRODUCT.</div>	<div>CAUTION: INTER-LUX IS NOT RESPONSIBLE FOR THE STRUCTURAL INTEGRITY OF THE BUILDING TO SUPPORT THE LUMINAIRE. ADDITIONAL BACKING MAY BE REQUIRED.</div>

WIRING DIAGRAM

