


20 Linear Direct / Indirect Suspended Round Opal Diffuser



Ordering Information							
Model	Fixation	Pattern	Length	Direct*	Indirect*	Finish	Options
WG-20LDI-S direct / indirect	48 96	S	A	Specify options using chart below* See ex 1: L1-D010-ROD	Specify options using chart below* See ex 2: M3-S-OD	W (std) B G F	DC



Luminaire

- Tubular design gives light in all directions, including behind the luminaire.
- End-to-end mounting gives uninterrupted lighting effect.
- Field replaceable LED boards.
- 90+ CRI, 3 steps MacAdam.
- Powder coat painted white - RAL 9010.

Fixation

- 48 = 48" suspension cable standard
- 96 = 96" suspension cable, field-cuttable

Pattern

- S = Straight run (continuous runs of any length available in 0.25" increments)

Length

- A = specify inches to the nearest 0.25" (i.e. 72.25")

Power¹

- L = 3.2W/ft low power (24V)
- M = 6.4W/ft mid power (24V)

CRI/CCT²

90+ CRI (Low/Mid Power)

- 927 = 2700K (243/449 lm/ft)
- 930 = 3000K (251/463 lm/ft)
- 935 = 3500K (256/473 lm/ft)
- 940 = 4000K (258/478 lm/ft)

*Direct/Indirect

Specify Power/CRI/CCT, Driver, Direct and Indirect Lens options

Power/CRI/CCT	Driver		Direct Lens	Indirect Lens
	L	M		
			X	ROD
				OD
927	L1	M1	S	SD
930	L2	M2	D010	
935	L3	M3	L3DAE	
940	L4	M4	L3DOE	
			DFPN	

Driver (remote)³

- X = No driver, ordered separately
- S = Standard driver 120-277V
- D010 = Osram, 10%, 0-10V dimming, 120-277V
- L3DAE = Lutron Hi-lume 1% EcoSystem, 120-277V
- L3DOE = Lutron Hi-lume Premier 0.1 EcoSystem, 120-277V
- DFPN = Lutron Forward Phase 1%, 120VAC

Direct Lens

- ROD = Round satin opal diffuser

Indirect Lens

- OD = Satin opal diffuser (standard)
- SD = Satin clear diffuser (high efficiency)

Finish

- W = White, 20% gloss, RAL9010 (standard)
- B = Black, 20% gloss
- G = Gray, 20% gloss
- F = Custom finished trim, specify RAL

Options

- DC = dual circuit

Emergency

- Emergency LED driver available, order separately.

¹ Wattage shown does not include power supplies/drivers.

² Delivered lumens with round opal diffuser shown for one direction.

³ Remote power supply required. See power supply page for details.

