



Ordering Information								
Model	Fixation	Pattern	Length	Power <sup>2</sup>	CRI/CCT <sup>3</sup>	Driver <sup>4</sup>	Lens	Finish
WG-100LDL-S								
WG-100LDL-S	48 (std) 96	S P <sup>1</sup> PZ <sup>1</sup>	A A x B A x B x C A x B x A x B	L M H	927 930 935 940	X SW D010 DALI LE	OD (std) SD	W (std) B G F

### Luminaire

- Suspended ceiling mount.
- Easily installed internal LED tray assembly with integral driver.
- High reflectance white reflector.
- Flush snap-in opal diffuser (standard).
- Powdercoat painted white - RAL 9010.

### Fixation

- 48 = 48" (1220mm) suspension cable (standard)
- 96 = 96" (2440mm) suspension cable, field-cuttable

### Pattern

- S = Straight run
- P = Standard patterns 2, 3 or 4 sided with 90° corners on the same plane<sup>1</sup>
- PZ = Non-standard patterns and/or corners other than 90° on multiple planes, consult factory<sup>1</sup>

### Length

- A, B, C = specify inches to the nearest 0.25" (6.35mm), i.e. 72.25" (1835mm)  
For patterns specify each length, i.e. 2 sided:  
A x B = 72.25" (1835mm) x 48" (1220mm);  
3 sided:  
A x B x C; 4 sided: A x B x A x B)

### Power<sup>2</sup>

- L = 10.5W/m low power (24V)
- M = 21W/m mid power (24V)
- H = 34W/m high power (24V)

### CRI/CCT<sup>3</sup>

- 90+ CRI (low/mid/high power)
- 927 = 2700K, (567/1052/1568 lm/m)
- 930 = 3000K, (587/1086/1617 lm/m)
- 935 = 3500K, (600/1105/1650 lm/m)
- 940 = 4000K, (603/1118/1666 lm/m)

### Driver (Integral)<sup>4</sup>

- X = Driver ordered separately
- SW = Switched/NON DIM
- D010 = 0-10/1-10V DIM
- DALI = DALI DIM
- LE = Leading-Edge DIM

### Lens

- OD = Satin opal diffuser (standard)
- SD = Satin clear diffuser (high efficiency)

### Finish

- W = White, 20% gloss, RAL9010 (standard)
- B = Black, 20% gloss
- G = Gray, 20% gloss
- F = Custom finished trim, specify RAL

### Emergency

- Emergency LED driver available, order separately.

<sup>1</sup> See pattern specsheet.

<sup>2</sup> Wattage shown does not include power supplies/drivers.

<sup>3</sup> Delivered lumens with satin opal diffuser shown.

<sup>4</sup> Remote power supply required. See power supply page for details.

