
20 Linear Recessed Flush Louver


whitegoods




Ordering Information									
WG-20LRF		S							
Model	Fixation	Pattern	Length	Power ¹	CRI/ CCT ²	Driver ³	Lens	Finish	Options
WG-20LRF	RPT RBT RRT RGT9 RGT15	S	А	L M	927 930 935 940	X SW DO10 DALI LE	LL45W LL45B	W (std) B G F	BEC FEC PEC

3.2in 81.7mm 81.7mm 4.4in 111.2mm


Recessed Plaster Trim (RPT)



Recessed Bezel Trim (RBT)



Recessed Return Trim (RRT)



Recessed Grid Trim (RGT9/RGT15)

Luminaire

- Continuous, Louver flush to the ceiling plane.
- Field replaceable LED boards.
- 90+ CRI, 3 steps MacAdam.
- Specify housing to nearest 0.25" (6.35mm), light insert delivered in 4.74" (120mm) increments.
- Standard and custom corners.
- Supplied with 4' (1220mm) class 2 plenum rated feed cable per fixture lengths.

Fixation

- RPT = Recessed plaster trim
- RBT = Recessed bezel trim
- RRT = Recessed return trim
- RGT9 = Recessed Grid Trim 9/16" (14mm)
- RGT15 = Recessed Grid Trim 15/16" (24mm)

Pattern

■ S = Straight run

Length

■ A = specify inches to the nearest 0.25"(6.35mm), 72.25" (1835mm), light insert delivered in 4.74" (120mm) increments.

Power¹

- L = 10.5W/m low power (24V)
- M = 21W/m mid power (24V)

CRI/CCT²

90+ CRI (low/mid power)

- 927 = 2700K (207/384 lm/m)
- \blacksquare 930 = 3000K, (213/394 lm/m)
- \blacksquare 935 = 3500K, (216/403 lm/m)
- \blacksquare 940 = 4000K, (219/407 lm/m)

Driver (remote)3

- X = Driver ordered separately
- SW = Switched/NON DIM
- D010 = 0-10/1-10V DIM
- DALI = DALI DIM
- LE = Leading-Edge DIM

Lens

- LL45W = Linear louver white
- LL45B = Linear louver black

Finish

- W = White, 20% gloss, RAL9010 (standard)
- B = Black, 20% gloss
- G = Gray, 20% gloss
- F = Custom finished trim, specify RAL

Options

- BEC = Bezel end caps
- FEC = Flat end caps
- PEC = Plaster-in end caps

Emergency

- Emergency LED driver available, order separately.
- ¹ Wattage shown does not include power supplies/drivers.
- $^{\rm 2}$ Delivered lumens with black louver shown.
- ³ Remote power supply required. See power supply page for details.