
# 20 Z Cove



Plaster Trim



**Bezel Trim** 



89mm


3.5" 89mm

2.8" 71mm

89mm


3.2" 81mm

## Plaster Trim (RPT)



3.2" 81mm

# Bezel Trim (RBT)



3.2" 81mm

4.76" 121mm

#### Grid Trim (RGT9/RGT15)

Ordering Information										
WG-20ZCF										
Model	Fixation	Pattern	Length	Power <sup>2</sup>	CRI∕ CCT³	Driver <sup>4</sup>	In-fill	Lens	Finish	Options
WG-20ZCF	RPT RBT RGT9 RGT15	S <sup>1</sup> PC <sup>2</sup> PR <sup>2</sup> PZ <sup>2</sup>	A A x B A x B x C A x B x A x B	L M H	927 930 935 940	X SW D010 DALI LE	X P4 P5	SD (std) OD	W (std) B G F	LEC REC LREC

## Luminaire

- Linear perimeter slot system featuring plaster-in or bezel precision knife edge for clean, minimal effect.
- Suitable for 5/8" (16mm) drywall ceiling.
- Lengths and angles factory cut to exact field dimensions.
- Mitered corners available with continuous LED illumination.
- Powder coat painted white RAL 9010
- Optional adjustable In-Fill panel to accomodate 4" (100mm) - 6"(150mm) slot.
- Micro-refractive satin diffuser guides light further down the wall.

## Fixation

- RPT = Recessed Plaster Trim
- RBT = Recessed Bezel Trim
- RGT9 = Recessed Grid Trim 9/16" (14mm)
- RGT15 = Recessed Grid Trim 15/16" (24mm)

## Pattern

- S = Straight run
- PC = Standard patterns coffer 2, 3 or 4 sided with 90° corners<sup>1</sup>
- PR = Standard patterns raft 2, 3 or 4 sided with 90° corners<sup>1</sup>
- PZ = Non-standard patterns and/or corners other than 90°, consult factory<sup>1</sup>

## Length

 A, B, C = specify inches to the nearest 0.25"(6.35mm), i.e. 72.25" (1835mm)
For patterns specify each length, i.e. 2 sided:
A x B = 72.25" (1835mm) x 48" (1220mm); 3 sided:

 $A \times B \times C$ ; 4 sided:  $A \times B \times A \times B$ )

# Power<sup>2</sup>

- L = 10.5W/m low power (24V)
- M = 21W/m mid power (24V)

# CCT / CRI<sup>3</sup>

90+ CRI minimum (Low/Mid)

- 927 = 2700K, (616/1141 lm/m)
- 930 = 3000K (636/1178 lm/m)
- 935 = 3500K, (649/1200 lm/m)
- 940 = 4000K, (656/1213 lm/m)

# Driver<sup>4</sup>

- X = Driver ordered separately
- SW = Switched/NON DIM
- D010 = 0-10/1-10V DIM
- DALI = DALI DIM
- LE = Leading-Edge DIM

# In-fill

- X = No in-fill panel
- P4 = 4" (100mm) 5" (130mm) adjustable in-fill panel
- P5 = 5" (130mm) 6" (150mm) adjustable in-fill panel

## Lens

- OD = Satin opal diffuser (standard)
- SD = Satin clear diffuser (high efficiency)

# Finish

- W = White, 20% gloss, RAL9010 (standard)
- B = Black, 20% gloss
- G = Gray, 20% gloss
- F = Custom finished trim, specify RAL

# Options

- LEC = Left end cap
- REC = Right end cap
- LREC = Left & Right end caps

# Emergency

 Contact factory for emergency lighting options

<sup>1</sup> See pattern spec sheet. Standard setup assumes the cove ends at a perpendicular wall and the led board is setback from the end to minimize light on the perpendicular wall. Contact us for options.

- <sup>2</sup> Wattage shown does not include power supplies/drivers.
- $^{\scriptscriptstyle 3}$  Delivered lumens with satin opal diffuser shown.

 $( \in$ 

# whitegoods